

Setting Guide

Thank you for buying the "INFOBAR A03" (simply called the "product" from here on). In this guide, settings and precautions for using the product are described. For explanations of basic functions, refer to "Basic Manual".

Company names and product names referred to in this manual are trademarks or registered trademarks of respective companies. The TM, ® marks may be omitted in this manual. Screen illustrations shown in this manual may look different from the actual screens. In some cases, minor details or a part of a screen may be omitted.

January 2015, 1st Edition

Sold by: KDDI CORPORATION • OKINAWA CELLULAR TELEPHONE COMPANY
Manufactured by: KYOCERA Corporation

- Basic Operation
Describes the basic operations.
- Initial settings
Make initial settings when you turn the power on for the first time.
- au Easy Setting
Set au ID.
- E-mail
Make initial settings for E-mail (@ezweb.ne.jp) etc.
- Making a call
Add a new contact to People to call.
- Receiving a call
Describes how to receive a call.
- Importing/Exporting contacts
Import/Export contacts using microSD™ memory card.
- Saving battery power
Describes the setting to save battery consumption using "Eco Mode".
- Setting Wi-Fi®
Describes how to connect Wi-Fi® network.
- Viewing/playing data
Describes how to view/play still images or video data.
- Infrared communication
Describes how to send/receive data between the product and another device using infrared communication function.

Basic Operation

For explanations of basic functions, refer to "Basic Manual".

Power key

Power ON
Press and hold (Power key) until the incoming (charging) light turns on

Canceling sleep mode
In sleep mode, press (Power key)

Power OFF
Press and hold (Power key) for at least one second, then [Power off] → [OK]

Canceling security on Start screen
Swipe (Flick) the screen

BACK BACK key
Return to the previous screen.

HOME HOME key
Display the iida Home. Long-touch to activate "Google".

RECENTS RECENTS key
Show recently-used applications. On the iida Home, long-touch to display iida Home settings.

Display

12:34
2015.11.11
WED

《Start screen》

Using Touch panel/Touch sensor key

Display and keys of the product (BACK / HOME / RECENTS) are touch panel and touch sensor keys. Touch with your finger to operate.

Tap/Double-tap
Lightly touch a screen or touch sensor key and then immediately release your finger. Double-tap is an operation of tapping the same point continuously twice.

Long-touch
Keep touching a screen or touch sensor key.

Flick (Swipe)
Touch the screen and flick up/down/left/right.

Slide
While your finger is gently touching the screen, trace it to the desired direction to move over.

Zoom-out/Zoom-in
Gently touch a screen with two fingers and widen or narrow the fingers' distance.

Drag
Gently touch the screen and them trace to the desired position.

Character entry

Use flick input or tap a key several times to enter characters.

Flick input
Long-touch a key to display enterable characters as shown in the right. Flick to the direction of the character to enter.

Character entry mode switch key
Tap to switch character type.

《Character entry screen (10-key)》

Initial settings

When you turn on the product for the first time after purchasing the product, follow the onscreen instructions to set language, functions and services.

Setting up Google account

Set up Google account to use Google applications such as "Gmail", "Play Store", "Hangouts". Setting items are as below (besides the items below, register "First" name and "Last" name).

User name	Register your Google account (user ID) and a character string for mail address. You can register a desired name, but a name already registered by another user cannot be set.
Password	Register password for the Google account.

1 Welcome
Select language, [▶]

2 Select Wi-Fi
Set up the Wi-Fi network to connect as required
* If you do not set up, tap "Skip".

3 Got Google?
On the Google account setting screen → [No] → [Get an account]
If you have a Google account, tap "Yes".

4 Your name
Enter "First" name and "Last" name → [▶]

5 Choose username
Enter a user name → [▶]
Checking registration of username starts.

6 Create password
Enter a password and reenter the password for confirmation → [▶]

7 Google password recovery
[Set up recovery options] → Enter spare mail address in case you forgot the password → [▶]
* If you have no another mail address, remain as blank.

8 Google services
Check the contents, then [▶] → [▶]

9 Finish account
Check the contents, then [I accept]

10 Authenticating...
Enter text displayed on screen → [▶]
* This screen may not be displayed.

11 Upgrade to Google+
Select if you join Google+
Tap "Not now" to go to the next here as explanation.

12 Set up payment info
Make purchase settings of Google Play as required

au Easy Setting

By setting au ID, you can use various services provided by au such as "au Kantan Kessai" which allows you to purchase applications from the auスマートパス (au Smart Pass) or Google Play. Main setting items are as follows.

au ID*	Register your au phone number or a character string for au ID (user ID).
au ID password	Register password for using au ID.

* "au ID" which is already used by another user cannot be set.

- If you skip the operation of "au Easy Setting" at that time, you can set au ID later. In such case, on the iida Home, → Tap "au Easy Setting" or "au ID Setting".

1 Welcome to au screen → [Next]

2 [Register "au ID" → [Next]

3 [au ID の設定・保存 (Set and save au ID)]

4 Enter the security code → [OK]
* Default value is a four-digit number written at subscription.

5 Enter a security password → [設定 (Settings)] → [終了 (Exit)]

6 [Update] → [Next]

7 Check the terms and conditions (reading requires), [Agree] → [Next]

8 [Agree]
Pre-configuration of Lookout for au is complete.

9 Select whether to restore data → [Next]
* If no data to restore, the screen does not appear.
* When a screen different from the above appears, follow the onscreen instructions.

10 Select a service to use → [Next]

11 Select apps to restore → [次へ (Next)]
* It is displayed only if you downloads from au website before.
* When a screen different from the above appears, follow the onscreen instructions.

12 Select apps to install → [次へ (Next)]
* When a screen different from the above appears, follow the onscreen instructions.
* Shown apps in おすすめアプリ (Recommended apps) may be different from the actual ones.

13 [Activate]/[Skip activation] → [Next]

14 [Finish]

E-mail

To use E-mail (@ezweb.ne.jp), subscription to LTE NET is required.

If you did not subscribe it when you purchased the product, contact an au shop or Customer Service Center. Your E-mail address is determined automatically after initial setting. You can change the E-mail address later.

Initial settings

1 On the iida Home [E-mail]

2 Check the contents, then [接続する (Connect)]

3 After E-mail initial settings, your E-mail address appears. Check E-mail address and tap "閉じる (Close)"

4 Check the content of "Information for improvement" → [Agree]/[Disagree] → [Done]

5 When the description screen for E-mail function appears, confirm the content and tap [Close]

Changing your e-mail address

1 On the iida Home [E-mail]

2 [E] → [E-mail settings]

3 [Other settings] → [接続する (Connect)]

4 [メールアドレスの変更へ (To Change E-mail address)]

5 Enter the security code → [送信 (Send)]

6 Check the contents, then [承諾する (I accept)]

7 Enter E-mail address → [送信 (Send)]

8 [OK]

9 [閉じる (Close)]

Backing up E-mail

You can back up E-mail.

Backed up data is saved on a microSD™ memory card (/storage/sdcard1/private/au/email/BU/) when a microSD™ memory card is attached. If a microSD™ memory card is not attached, data is saved on the internal storage (/storage/sdcard0/private/au/email/BU/).

1 On the iida Home [E-mail]

2 [E] → [E-mail settings]

3 [Backup/Restore]

4 [Mail Backup] → Confirm


5 Select a character code to make backup data → [OK]

6 Select a mail type to back up → [OK]


PC-mail settings
You can use mail addresses except for E-mail (@ezweb.ne.jp). You need to set up a PC-mail account to use PC-mail. For the first time use, make settings as follows.
On the iida Home → [Mail] → Enter Email address and password → [Next] → Set account → [Next] → Enter account name etc. → [Next]


Making a call


■ Adding new contact and making a call


1

On the iida Home, [People]

2

[Create a new contact] → [OK]
When All contacts appears, tap .

3

[]

■ Making a call from Recent calls

1

On the iida Home, [Phone] → Tap "Recent calls" tab

2

[] of a party to call

Checking your own phone number (Profile)
Operate as follow to check your own phone number.

On the iida Home, [Settings] → [Profile] → Profile screen appears.

Changing your E-mail address
Your E-mail address can also be checked on profile screen.
If you make initial settings for [E-mail] app as follows, the E-mail address of E-mail (@ezweb.ne.jp) can be automatically registered to profile screen.

On the iida Home, → [E-mail] → [Connect] → [閉じる (Close)] → Registered to profile screen.

Receiving a call

You can receive a call in the following steps.
* "Display the popup on an incoming call" is set to "ON" in Sync Call settings by default.

■ Calling

When "Display the popup on an incoming call" is set to "ON" in Sync Call settings

1

Receiving screen → [Accept]
Tap  to hide balloon.


2



Calling starts

3

To end the call, [End]

In sleep mode or when Start screen is displayed

1

Receiving screen, slide right from "  " to "  "

2


Calling starts

3


To end the call, [End call]

■ Answering with Auto answering


Answer by the answering memo message and record a message of the party when you cannot answer calls.

1


Receiving screen → [Phone Screen]

2


Drag the operation panel down



3

[Menu] → [Reply Auto answering]

4

The caller hears the guidance

5


To answer the call, slide right from "  " to "  "

Importing/Exporting contacts


You can import/export contacts from/to the internal storage or microSD memory card

■ Importing


For the first time importing contacts, operate as follows.

1


On the iida Home, [People]

2

[Import contacts]
When contacts are already saved, see "■ Importing/Exporting".

3


[Import from SD card]
If contacts file (vCard) is only one, importing starts.

4


Select a method → [OK]
→ Select vCard → [OK]

■ Importing/Exporting


When contacts are already saved, operate as follows.

1


On the iida Home, [People]

2


→ [Import/Export]

3


[Import from Internal storage]/[Import from SD card]

4


Select a method → [OK] → Select vCard → [OK]

3

[Export to Internal storage]/[Export to SD card]

4


Select contacts → [OK]
Select [Select all] to export all contacts.

5


[OK]

Saving battery power


Use "Eco Mode" to set sleep time of backlight and screen brightness to the minimum value or to enable/disable Auto-rotate screen, Wi-Fi®, MaxiMZR, Bluetooth®, Location access, Reader/Writer, P2P, use of Pedometer, CPU clock restriction, Data communication, etc. so that you can save the battery power. When the battery power is low, set "Data communication" to "OFF" and limit communications only for calling to extend standby time.

1

iida Home, [Eco Mode]

2

[Custom]/[Long life]


Tap "  " of "Custom"/"Long life" to check or change the battery saving items.

Setting Wi-Fi®


Use your home Wireless LAN (Wi-Fi®) or public wireless LAN to connect to the Internet services.
Main settings are as follows.

Easy setting by camera	Use for registration of an access point compatible with "Easy setting by camera".
WPS system	Use for registration of access point compatible with Wi-Fi Protected Setup™ with WPS mark.


* If you turn on wireless LAN (Wi-Fi®) function, battery consumption increases. You are recommended to turn wireless LAN (Wi-Fi®) function to OFF when not using wireless LAN (Wi-Fi®) function.

1


On the iida Home, [Settings]

2


[Wi-Fi]
Available Wi-Fi networks are detected automatically and their network SSIDs appear in the Wi-Fi networks.

3


[Wi-Fi EASY SETTINGS]

When access point is not detected, tap "  " to add access point manually.


■ Using Wi-Fi connection tool by the camera

4

[Easy setting by camera]


5

Select the set place


6

Follow the onscreen instructions to register an access point.


■ Using WPS system access point

4


[WPS button]

5

Keep pressing WPS button of access point to set to WPS mode. An access point is automatically detected and registration starts.

4

[WPS Pin Entry]


5

Enter displayed PIN code for access point, then registration starts.


Viewing/playing data

By transferring data from the previously used au phone to a microSD™ memory card, you can view/play* still image or movie data using "Photos in the product.

* Copyrighted data on the previously used au phone cannot be transferred to the product. However, some Chaku Uta Full®, Video Clip, Chaku Uta Full Plus® may be able to be transferred and played on the product with the same phone number by backing up with LISMO Port Ver 4.2 or later.

1

On the iida Home, [Photos]

2

Tap data to be displayed
Data is played.


Backing up by au Backup App
You can back up/restore various data saved on your smartphone to microSD™ memory card by downloading au Backup App. Backup data of your old terminal can be completely migrated. Also, the contacts on a feature phone can be migrated easily. For details about downloading etc., refer to au homepage. <http://www.au.kddi.com/mobile/service/smartphone/safety/backup/>

Infrared communication


You can send/receive profiles or various data between the product and another device using infrared communication.

* When "Reader/Writer, P2P" is ON, "Infrared" app is not available.
To turn off, on the iida Home, [Settings] → [More...] → [NFC/OsaiFu-Keitai Settings] → Tap [Reader/Writer, P2P] to unmark


■ Receiving data

1

On the iida Home, [Infrared]


2

[Receive]


3

Point the infrared data port of the product to the infrared data port of the other device.
When authentication code entry screen appears, enter authentication code (four-digit number) → [OK].


■ Sending data

1


On the iida Home, [Infrared]

2

[Send profile]/[Send contacts]/[Send file]
If you tap "Send profile", data transfer starts.

3

Select a data item to send → [OK]

4

Point the infrared data port of the product to the infrared data port of the other device.